

	SYSTEM PROGRAMING (must be @ EXT 10 or 11) - Feature 00>left intecom twice
101	System Date
103	System Time
104	Number of Lines
105	Tranfer Return Rings (0-9 rings, 4 rings, 0 rings = no return_
110	AutoSystem Answer # of Rings Delay THIS HAS NOTHING TO DO WITH VOICE MAIL
111	AutoSystem Button THIS HAS NOTHING TO DO WITH VOICE MAIL
112	Direct Extension Dial Delay # of Ring Delay THIS HAS NOTHING TO DO WITH VOICE MAIL
113	Direct Extension Dial Button THIS HAS NOTHING TO DO WITH VOICE MAIL
115	Wake Up Service Button (1- asg, 2-not asg, 3-select button)
119	Ring on Transfer (1- Active, 2-Not Active)
123	Backup programming Automatic (1-internal, 2-PC Card, 3-Not Active)
124	Backup programming Manual (1-internal, 2-PC Card - press ENTER to begin)
125	Restore Programing (1-Internal Man.mmddy, 2-PC Card Man.mmddy, 3-Internal Auto.mmddy, 4-PC Auto.mmddy)
126	Auto Daylight Savings time (1-Active)
127	Hold Reminder time (0=Not Active, 1-10sec, 2-20 sec, 3-30sec, 4-45sec, 5-60sec, 6-90sec, 7-120sec, 8-150sec) 9-180sec)
209	Unique Line Ring Dial line # (1, 2-8)
306	Transf Return Ext. - Dial Ext # then Ext# to Ext tranf ext should return to if not answered
308	Dist Ext Ringing (Dial Ext # then 1-active, 2-not active)
311	External Hot Line (Dial Ext# then 1-assigned, 2-not assigned)
312	Voice Interupt on Busy (Dial Ext# then 1-assigned, 2-not assigned)(may SET UP BUTTON Talk-back Feature 18)
322	Remote Call Forwarding (Ext to ext)
403	System Password (dial 4 digits)
404	Dissallow List
405	Dissallow List assignment to extensions
406	Emergency Phone # List
407	Allow List
408	Allow List Assignment
409	Force account Code List (list 1-99) (up to 6 digits)
307	Forced Act Code EXT# (1-assigned, 2-not assigned) (SET UP BUTTON Feature 12)
399	Copy Settings (Dial Sorce Ext # then target Ext #)
501	Pickup Group Ext (dial a group 1-4, dial Ext #, 1-assign to group, 2-not assigned)
502	Calling Group Extensions (dial a group 1-4, dial Ext #, 1-assign to group, 2-not assigned)
<i>Feature 23</i>	<i>Caller ID Logging Button</i>
318	<i>Call ID Line Association (Enter Extension & Line per each Caller ID Line)</i>
319	<i>Caller ID LOG All Calls (@Data Enter ext##) - Program one-touch button Feat 23</i>
124	Backup Programing - Manual, Begin ACTIVATE THIS ONCE ALL PROGRAMING IS COMPLETE
125	Restore Programing mmddy
209	Unique line ringing
301	Line Assignment
302	Line Access restriction 1-no restr, 2-outg, 3-Incom, 4-no acc IMPORTANT FOR FAX LINE
304	Automatic Extension Privacy
401	Outgoing Call Restriction 1-No restr, 2-intercome only, 3-local calls only TOLL RESTRICT
502	Calling Group - Assign Ext to Paging Calling Group
989	Restore to default - must also enter 25327
	Then back up from internal memory #124
	Do this twice
603	Hot Line Ext (NOT 10 OR 11) Dial hot line ext# then dial alerted Ext# or 70 to paging system (Use Remove button to remove)
604	Door Phone 1 Ext

	605	Door Phone 2 Ext
	606	Door Phone allert ext
	503	Night Service Button <i>MUST BE ASSIGNED TO SCHEDULE WHEN VMS COVER SCHEDULE will activate</i>
	504	Night Service Extensions assignment
	507	VMS Cover Schedule 1-Always, 2-Day Only, 3-Night Only
	505	Hunt Group - 7 for VMS, ext 78 and 79 for Partner PCMCIA Mail (4 port & 16 port) <i>MUST ASSIGN FOR VOICE MAIL</i>
	206	Group Call Distribution 7>line (01)>1-Assigned for each line VMS is to Cover when VMS Schedule (507) is programmed
	310	Automatic VMS Cover, <i>MUST ASSIGN FOR EACH EXTENSION WITH VOICE MAIL</i>
	117	VoiceMail Cover # of Ring Delay
	321	VMS Cover rings (3-standard, 1-9 rings before VM Answers)
	Feature 01	Do Not Disturb
	Feature 02	Exclusive HOLD
	Feature 03	Recall - FLASH HOOK
	Feature 04	Save Number
	Feature 05	Last # Redial
	Feature 07	Privacy (If not assigned Automatic Extension Privacy)
	Feature 12	Account Code Entry Button
	Feature 11	Forward Extension
	Feature 13	Manual Signaling (Feature 13, then ext#)
	Feature 17	Caller ID Inspect
	Feature 18	Talk back on Voice Interrupt On Busy
	Feature 19	Background Music
	Feature 16	Caller ID Name Display
	Feature 23	Caller ID Logging Button
	Feaure 24	record a Call
	Intercom 70	Loud Speaker Only
	Intercom *70	Simultaneous Loud Speaker AND Calling Page Group 1
	Intercom *71	Page Group 1
	Intercom *72	Page Group 2
	Intercom 6, EXT#)	CALL PICK UP
	Intercom 8, EXT#)	Direct Line Pick Up
		Group Calling Ring - Program button Feature 7 (Group(1-4)) for Calling Group
		Group Calling PAGE - Program button Feature *7 (Group(1-4)) for Paging Group
		Group Hunting Ring to 1st available ext- Program button Feature 77 (Group(1-7)) for Calling Hunt Group
		Group Hunting Page to 1st available ext- Program button Feature * 77 (Group(1-7)) for Paging Hunt Group
		Group Pick Up - Program button - Intercom 66 , then Pickup Group 1-4
		Help Desk queue w ext 20, 21, 22, 23
	Hunt group	#505>2>assign ext 20-23 AND unsed ext 57)
	ans Rtrn Rings	#105>0-rings
	Ring On Transf	#119>2 -not active